



“ETR” AM/FM Tuner



ETR Black finish



ETR Chrome finish

General Description

The Perreaux “ETR” incorporates the latest technology in AM/FM tuner design including a dual gate MOSFET front end producing low noise and high gain reception even in low signal strength areas. For easy recall of favourite stations the ETR has 30 separate memory presets. Tactile switches are provided on the front panel for all basic tuner functions with additional convenience controls available on the full function Remote Control. All units are optimised to suit the broadcast standards of the country it is exported to. Again, the same superb quality of construction as the other Perreaux ‘E Series’ components.

Features

1 pair Unbalanced Line Outputs (RCA)
 Full Function Remote Control
 30 Station Presets
 Auto-Search Tuning
 Preset Scanning

RDS and RBDS Capability
 Stereo/Mono Switching
 Dual Gate MOSFET Front End
 High Gain Reception
 12V Remote Trigger

Specifications

FM Section (75 ohm antenna)

Usable Sensitivity:..... 14.2dBf
 50dB Quieting Sensitivity:
 Mono 20.2dBf
 Stereo..... 45.3dBf
 Signal to Noise Ratio (@ 65dBf):
 Mono73.0dB
 Stereo.....70.0dB
 Harmonic Distortion (@ 65dBf):
 Mono0.2%
 Stereo.....0.3%
 Frequency Response:.... 10Hz-15kHz, ± 3.0 dB
 Capture Ratio:2.0dB
 Spurious Response Ratio:90.0dB
 Image Rejection Ratio:.....80.0dB
 IF Rejection Ratio:80.0dB
 AM Suppression Ratio:55.0dB
 Output Level:..... 1.0V

AM Section (loop antenna)

Usable Sensitivity:.....500 μ V/m
 Selectivity:..... 25.0dB
 Harmonic Distortion:.....0.5%
 Image Rejection Ratio:..... 45.0dB
 Signal to Noise Ratio:..... 40.0dB
 Output Level:..... 500mV

General

Power Consumption: 12W
 Dimensions (not including feet and terminals):
 Width 425mm (16.7")
 Height 88mm (3.5")
 Depth 315mm (12.4")
 Weight 7.0kg (15.4lb)